



CHROMATEQ

DJ, Entertainment, Live

10th
YEAR
ANNIVERSARY

Main Features

	LP 128	LP 512	CLUB 1024	PRO NET	PIXXEM 128	PIXXEM 255
DMX (Software & Live)						
LED PLAYER in/Out	128	512	1024	1024	1024	1024
PRO DMX in/Out	128	256	1024	1024	1024	1024
PIXXEM in/Out			1024	1024	1024	1024
Max Device Connected (USB)	12	12	12	12	12	12
STAND ALONE						
DMX Out (16-bit channels)	128	512	512	512	512	512
Zone (Scene play a time, Stand Alone)	1	1	1	1	1	1
MEMORY (Stand Alone)						
Memory Step capacity	512 ~ 1024	100 ~ 1024	100 ~ 1024	100 ~ 1024	100 ~ 1024	100 ~ 1024
Max Scene capacity	255	255	255	255	255	255
TRIGGERS (Stand Alone)						
Smart Contacts (on/off, release, start)	4 (15 max)	4 (15 max)	4 (15 max)	4 (15 max)	4 (15 max)	4 (15 max)
Infrared remote	Y	Y	Y	Y	Y	Y
Next Scene Button	Y	Y	Y	Y	Y	Y

Software Option

	LP 128	LP 512	CLUB 1024	PRO NET	PIXXEM 128	PIXXEM 255
SOFTWARE (Live)						
Max Page / Tab	5 (Player)	5 (Player)	512	512	512	512
Timeline Audio, Video Synch (Pro DMX)			30 mm	24 h	24 h	24 h
Studio DMX 3D View	Y	Y	Y	Y	Y	Y
User Interface Customization	Y	Y	Y	Y	Y	Y
Pro Options (Live)			Optional	Y	Y	Y
PIXXEM						
DVI Resolution			128*128	1024*768	1280*720	1280*1024
DVI Pixels			16384	786432	921600	1310720
Timeline Audio (Synchro. 24h)				Y	Y	Y
TRIGGERS (Live)						
MIDI, RS232, DMX IN, Wi-Light 2	Y	Y	Y	Y	Y	Y
UDP / Ethernet Triggers	Y	Y	Y	Y	Y	Y
Shortcut Keys & Hyperlink	Y	Y	Y	Y	Y	Y
MIDI Control, Audio Beat, BPM	Y	Y	Y	Y	Y	Y
PRO OPTIONS (Live)						
Timeline Live Record		Optional	Optional	Y	Y	Y
Multiple Timeline and Import		Optional	Optional	Y	Y	Y
MTC, MIDI, Time Code		Optional	Optional	Y	Y	Y
PC Clock & Calendar Trigger		Optional	Optional	Y	Y	Y
Art-Net INPUT & Trigger		Optional	Optional	Y	Y	Y
ART-NET (Software & Live)						
Art-Net (Player, Pro)		512	2x512	16x512	64x512	64x512
Art-Net (PIXXEM)			8x512	64x512	128x512	255x512
Art-Net + DMX			Y	Y	Y	Y
Art-Net INPUT				Y	Y	Y

All our packages match the requirements for Live, Sound to light, Stage, Entertainment, Architectural, and Installations.

5 years international warranty
Free software updates and download

ART-NET: Live Art-Net signal is output from the computer Ethernet network card and its RJ45 port.

Operating temperatures : -25C° to +85C°

System Requirements for Software and App:

Windows 7, 8, 10, MAC Os X, Linux, Raspberry
32 and 64 bits compatible
2 Ghz CPU, 4 Gb RAM, 1 USB port
600 Mb Disk space
1 Ethernet port (Art-Net and sACN)
1920x1080 Display resolution (recommended)

APP:

Android (5.0 and +), iOS 12 and higher, iPad OS
1.5 Ghz CPU
60 Mb Disk space
1280x800 Display resolution
WIFI 802.11 b/g/n



CHROMATEQ

Architectural, Installation

10th
YEAR
ANNIVERSARY

Main Features

	DIN 1024	SLIM 512	CQSA 512	SLIM 1024	CQSA 1024	CQSA-E 1024
DMX (Software & Live)						
LED PLAYER in/Out	1024	512	512	1024	1024	1024
PRO DMX in/Out	1024	512	512	1024	1024	1024
PIXXEM in/Out			512		1024	1024
USB + Ethernet						Y
Max Device Connected (USB)	12	12	12	12	12	12 / 128 (Ethernet)
STAND ALONE						
DMX Out (16-bit channels)	1024	512	512	1024	1024	1024
Zone (Scene play a time, Stand Alone)	1	1	1	5	5	5
Art-Net (Stand Alone, SD card)						8 x 512 Out
NODE (Art-Net to DMX decoder)						2 x 512 Out
Max Device Connected for DMX Out	32	32	32	32	32	32 / 128 (Ethernet)
MEMORY						
Memory Step capacity	2K ~10K	5K ~20K	5K ~20K	2K ~10K	2K ~10K	2K ~10K
Max Scene capacity	255	512	512	512	512	512
SD Card (Class 10 Micro SD)		Y	Y	Y	Y	Y
TRIGGERS (Stand Alone)						
Buttons (modes, valid, select x8)		Y	Y	Y	Y	Y
RTC (Built in Clock and Calendar)	Y	Y	Y	Y	Y	Y
Wi-Light APP, UDP, JSON (Ethernet)						Y
Smart Contacts (on/off, release, start)	15	5 (31 max)	7 (127 max)	5 (31 max)	7 (127 max)	7 (127 max)
RS232 (Stand Alone + Live)	Y		Y		Y	
DMX In & Merge DMX	Y			Y	Y	Y
Master/Slave (Wired, 32 Devices max)	Y	Y	Y	Y	Y	Y + Ethernet (x128)
Mode & Manual Clock setting		Y	Y	Y	Y	Y
Infrared remote	Optional	Optional	Optional	Optional	Optional	Optional
Light Intensity	Optional	Optional	Optional	Optional	Optional	Optional

Software Option

	DIN 1024	SLIM 512	CQSA 512	SLIM 1024	CQSA 1024	CQSA-E 1024
SOFTWARE (Live)						
Max Page / Tab	512	512	512	512	512	512
Timeline Audio, Video (Pro DMX)	30 mn	30 mn	30 mn	30 mn	30 mn	30 mn
Studio DMX 3D View	Y	Y	Y	Y	Y	Y
User Interface customization	Y	Y	Y	Y	Y	Y
Pro Options (Live)	Optional	Optional	Optional	Optional	Optional	Optional
PIXXEM						
DVI Resolution			64*64		128*128	128*128
DVI Pixels			4096		16384	16384
TRIGGERS (Live)						
MIDI, RS232, DMX IN, Wi-Light 2	Y	Y	Y	Y	Y	Y
UDP / Ethernet Triggers	Y	Y	Y	Y	Y	Y
Shortcut Keys & Hyperlink	Y	Y	Y	Y	Y	Y
MIDI Control, Audio Beat, BPM	Y	Y	Y	Y	Y	Y
ART-NET (Software & Live)						
Art-Net (Player, Pro)	2x512	512	512	2x512	2x512	2x512
Art-Net (PIXXEM)			4x512		8x512	8x512
Art-Net + DMX		Y	Y	Y	Y	Y
Art-Net INPUT						Y

2010-2021 Chromateq SARL
Chromateq is a registered trademark

191 Allée de Lauzard
34980 St Gély du Fesc, FRANCE
Web: www.chromateq.com
Email: info@chromateq.com
Phone: +33 952210755
Wechat: Chromateq
WhatsApp: +8613422062209
QQ: 2908265661

Software & App download:

Software package download: <https://www.chromateq.com>
Wi Light 2 app download (iOS): <https://apps.apple.com/us/app/wi-light-2/id1523046687?l=fr>
Wi Light 2 app download (Android): <https://play.google.com/store/apps/details?id=com.chromateq.wilight2>

<https://www.facebook.com/ChromateqCompany/>
 <https://twitter.com/Chromateq>
 <https://www.youtube.com/c/chromateq>



FREE

