

Worldwide supply and support *since 2010*



PRO DEX 2



PIXXEM



WI-LIGHT 2

**FREE** cross-platform software.  
User friendly, customizable, LIVE and Stand Alone.





### CLUB



### CLUB-E



### CQSA / CQSA-E



### LIVE & STAND ALONE WITH XLR

	CLUB 128	CLUB 512	CLUB-E 1024	PRONET-E	CQSA 512	CQSA 1024	CQSA-E2 1024
Retail Price (EUR / USD)	€109 / \$119	€199 / \$219	€299 / \$329	€449 / \$499	€299 / \$329	€399 / \$439	€449 / \$499
DMX Out (Live / Stand Alone)	128	512	2x512		512	2x512	
Upgradable on site *	Yes						
Ports	USB-C		USB-C + Ethernet		USB-C		USB-C + Ethernet
XLR	1x3 Pins		2x3 Pins				
Buttons				1	12		
Smart Contacts Port (5V)	3		7				
RS232 Triggers					Yes	Yes (In / Out)	
International Warranty	1	3	5				

\* Upgradable on site: Upgrades can be done on site directly and purchase by email. Interface serial number, customer email and upgrade reference are required to send the upgrade file to customers. DEVICETOOL is required to upgrade products with the upgrade file. The DEVICETOOL is in the software directory. 512CH and U2 Upgrades are cumulative and give the total number of universes or DMX channels.

### LIVE WITH SOFTWARE & COMPUTER

	CLUB 128	CLUB 512	CLUB-E 1024	PRONET-E	CQSA 512	CQSA 1024	CQSA-E2 1024
PRO DMX 2 + PIXXEM + STUDIO DMX *	Yes	Yes	+30 Mn Timeline	FULL	+30 Mn Timeline	+30 Mn Timeline	FULL
Art-Net Universes	Optional			1 in, 2 Pro2, 4 Pixxem	Optional		2 SA, 1 in, 2 Pro2, 4 Pixxem
Max DMX / Art-Net Universes in/out	16 in, 64 Pro2, 512 Pixxem, 64 Studio						
DMX In	128	512	512 + RDM	512	512	512 + RDM	
MIDI, Audio Beat, Level & Synch.	Yes						

\* License Key File: FULL Software Upgrade and Art-Net Universes Upgrades exist as License Key File to install on a single computer and unlock the software. License Key files require the computer configuration .UKD to be generated.

FULL: + RDM + 24hTimeline + Multi timeline + Timeline Live record + 3D unlimited + MIDI Time Clock + SMPTE + PC Calendar & Clock Triggers.

### STAND ALONE, interface programmed with PRO DMX 2

	CLUB 128	CLUB 512	CLUB-E 1024	PRONET-E	CQSA 512	CQSA 1024	CQSA-E2 1024
Power	5-12V	5-12V	5V	5V	5-24V	5-24V	5-24V
Memory	40KB	40KB	200KB	200KB	8 MB / SD card	8 MB / SD card	8 MB / SD card
Zone and Scene	1			5			
Max Scene number	512			5x512			
ArtNet Out on SD card							2x512 (8 max)
Wi Light APP / API and UDP Triggers				Yes, LAN	Yes, LAN + WEB		
DMX In Triggers / Merge							512
Calendar, Clock, Brightness Triggers							Yes
Infrared Triggers and Remote	Yes		Optional				
Master / Slave Synchro & Triggers							Yes

**Mobile minimum configuration :**  
Android 5 / iOS 10 and +  
1Ghz CPU, 1 Gb RAM, 60 Mb disk

**Configuration minimale PC:**  
Windows, Mac OS, Linux (32 and 64 bits)

2Ghz CPU (2 cores), 8 Gb RAM  
2Gb RAM graphic card (for 3D only)  
600 Mb disk, 1920x1080 resolution  
1 USB port (device)  
1 Ethernet port (for Art-Net & sACN)



### DIN-E



### TOUCH



### SLIM



### LIVE & STAND ALONE WITH TERMINAL BLOCKS

	DIN-E 512	DIN-E 1024	DIN-E 2048	TOUCH 512	TOUCH 1024	SLIM 512	SLIM 1024
Retail Price (EUR / USD)	€299 / \$329	€399 / \$439	€599 / \$559	€299 / \$329	€399 / \$439	€299 / \$329	€399 / \$439
DMX Out (Live / Stand Alone)	512	2x512	4x512	512	2x512	512	2x512
Upgradable on site *	Yes						
Ports	USB-C + Ethernet			USB-C			
Terminal Blocks	Yes						
Smart Contacts Port (5V)		12		4			5
RS232 Triggers In / Out		Yes					
Tactile Glass Panel				Yes			
International Warranty				5			

\* Upgradable on site: Upgrades can be done on site directly and purchase by email. Interface serial number, customer email and upgrade reference are required to send the upgrade file to customers. DEVICETOOL is required to upgrade products with the upgrade file. The DEVICETOOL is in the software directory. 512CH and U2U Upgrades are cumulative and give the total number of universes or DMX channels.

### LIVE WITH SOFTWARE & COMPUTER

	DIN-E 512	DIN-E 1024	DIN-E 2048	TOUCH 512	TOUCH 1024	SLIM 512	SLIM 1024
PRO DMX 2 + PIXXEM + STUDIO DMX *	+30 Mn Timeline	+30 Mn Timeline	FULL	+30 Mn Timeline	+30 Mn Timeline	+30 Mn Timeline	+30 Mn Timeline
Art-Net Universes	Optional	2 SA, 1 In, 2 Pro2, 4 Pixxem	8 SA, 4 In, 8 Pro2, 16 Pixxem	Optional			
Max DMX / Art-Net Universes in/out	16 In, 64 Pro2, 512 Pixxem, 64 Studio						
DMX In	512	512 + RDM		512	512 + RDM		512
MIDI, Audio Beat, Level & Synch.	Yes						

\* License Key File: FULL Software Upgrade and Art-Net Universes Upgrades exist as License Key File to install on a single computer and unlock the software. License Key files require the computer configuration .UKD to be generated

FULL: + RDM + 24hTimeline + Multi timeline + Timeline Live record + 3D unlimited + MIDI Time Clock + SMPTE + PC Calendar & Clock Triggers.

### STAND ALONE, interface programmed with PRO DMX 2

	DIN-E 512	DIN-E 1024	DIN-E 2048	TOUCH 512	TOUCH 1024	SLIM 512	SLIM 1024
Power	5-24V						
Memory	8 MB / SD card						
Zone and Scene	1	5		1	5	1	5
Max Scene number	512	5x512		512	5x512	512	5x512
ArtNet Out on SD card	Optional (8 Max)	2x512 (8 max)	8x512				
Wi Light APP / API and UDP Triggers	Yes, LAN	Yes, LAN + WEB					
DMX In Triggers / Merge		512			512		512
Calendar, Clock, Brightness Triggers	Yes						
Infrared Triggers and Remote	Optional						
Master / Slave Synchro & Triggers	Yes						





### Hardware and Software Upgrades

Reference	Software and DMX Upgrades		Art-Net Upgrades for all interfaces					
	FULL	512CH	U2U	U8U	U16U	U64U	U256U	U512U
Upgrades* (EUR / USD)	149 €	99 €	€99 / \$109	€199 / \$219	€299 / \$329	€699 / \$759	€1099 / \$1199	€2199 / \$2399
ArtNet Out - PIXXEM		Add 512 DMX chan- nels	4	16	32	128	256	512
ArtNet Out - PRO DMX 2			2	8	16	64	64	64
ArtNet SA on SD card			2	8	8	8	8	8
ArtNet Input			2	8	16	16	16	16
Resolution DVI (PIXXEM)			Per Upgrade (Up to 2048)		16384 px 128 x 128	307200 px 640 x 480	921600 px 1280 x 720	1310720 px 1280 x 1024
Audio & Video Timeline	24h		30mn	24H	24h	24h	24h	24h
Software + Studio 3D	FULL		Per Upgrade	FULL	FULL	FULL	FULL	FULL

\* Upgradable on site: Upgrades can be done on site directly and purchase by email. Interface serial number, customer email and upgrade reference are required to send the upgrade file to customers. DEVICETOOL is required to upgrade products with the upgrade file. The DEVICETOOL is in the software directory. 512CH and U2U Upgrades are cumulative and give the total number of universes or DMX channels.

FULL: + RDM + 24hTimeline + Multi timeline + Timeline Live record + 3D unlimited + MIDI Time Clock + SMPTE + PC Calendar & Clock Triggers.

### License Keys for computers

Reference	L2U	L8U	L16U	L32U	L64U	L255U	L512U
License Keys (EUR)	249,00 €	399,00 €	499,00 €	649,00 €	799,00 €	1 199,00 €	2 299,00 €
ArtNet Out - PRO DMX 2	2	8	16	32	64	64	64
ArtNet Out - PIXXEM	4	16	32	64	128	255	512
ArtNet Input	2	8	16	16	16	16	16
Software + Studio 3D	30mn Timeline	FULL	FULL	FULL	FULL	FULL	FULL

Licenses Key files are use to unlock the Chromateq's softwares without any hardware / device / interface are connected to the computer.  
All License Key are install permanently on a single computer only with a warranty of 3 years.  
To be generated, license Key files require the computer configuration file given by the Chromateq software.

- LAN: WI Light 2 APP / API compatible with Stand Alone -E interfaces in local network
- WEB: WI Light 2 APP / API compatible with Stand Alone -E interfaces over internet with an user account
- B / W: Black or White housing color available
- XLR / TB: XLR or Terminal Block connectors available
- XLR 3/5: 3 or 5 PINs XLR available before purchase

**Art-Net Out on SD:** Art-Net data is save on micro SD card and play back Stand Alone without computer from the interface. Art-Net signal is sent to the network from the RJ45 ethernet port of the interface.

**Art-Net Live:** Art-Net signal is sent to the network from the software and computer RJ45 Ethernet port.

**Infrared:** Infrared LED to receive commands and triggers from the Infrared Remote.. Need the IR Kit with 2 Remotes and Infrared external PCB.

**RS232:** Device can receive some orders and commands listed in the Stand Lone mode of the software and datasheet. Out option can send a specific sequence of characters to another RS232 compatible device.

**Master / Slave:** Communication port between several interfaces (up to 32, 20m max) to synchronize data, scene , steps and triggers. LTP, Desynchronize and more options are also available.

**Calendar, Clock, Brightness:** Scenes can be trigger On/Off by Time, Date or according to the Light Intensity

**Smart Contacts:** Port of the interface to receive simple dry contact actions when connected to 5V DC. Can Trigger On, On/Off, Release (On when contact is don, Off when contact is release), Restart, Hold contact (Dimmer +, Speed, next scene), Priority, Start and Stop and play scene options

**UDP:** Open Ethernet protocol under UDP format to send commands to the Chromateq software and Chromateq Ethernet devices, Requir to choose the IP address to send the UDP commands.

**Wi-Light 2APP / API:** Easy application for iOS and Android mobiles and tablets. Can control the interface and the software with triggers action and simple commands actions and DMX level on channels.

### Free Software & Application :

Software package & APP/API : <https://chromateq.com/dmx-software-downloads/>

2010 - 2025 Chromateq SARL - Chromateq - All rights reserved

